

Advanced Programming and Reports ER-180T

Changing the Department Tax & Price status

all Departments and PLUs default to open price and price entry is compulsory. If change of status is needed, see Department(s) and PLU(s)programming. The status and price programming are bound together.

The steps for changing the tax and price status are in the setup guide. Below are 2 examples:

1. Make a department 1 button "Preset price with NO GST"

- Turn the "C" Key to the PGM position
- 500, [SubTL]
- [DEPT 1] [0][0][0][0][1][0][0][1]
- [X/Time]
- [Cash/TTL]

2. Make a department 2 button "Open price with NO GST"

- Turn the "C" Key to the PGM position
- 500, [SubTL]
- [DEPT 2] [0][0][0][0][1][0][0][0]
- [X/Time]
- [Cash/TTL]



Changing the Department Tax & Price status

all Departments and PLUs default to open price and price entry is compulsory. If change of status is needed, see Department(s) and PLU(s)programming. The status and price programming are bound together.

The steps for changing the tax and price status are in the setup guide. Below are 2 examples:

1. Make a department 1 button "Preset price with NO GST"

- Turn the "C" Key to the PGM position
- 500, [SubTL]
- [DEPT 1] [0][0][0][0][1][0][0][1]
- [X/Time]

- [Cash/TTL]

2. Make a department 2 button “Open price with NO GST”

- Turn the “C” Key to the PGM position
- 500, [SubTL]
- [DEPT 2] [0][0][0][0][1][0][0][0]
- [X/Time]
- [Cash/TTL]

Edit

changing the name of a function key

Turn Key to PGM

1. 80 [SUBTL]
2. Enter new description using the letter keys AND THEN press the department key you want change (Max 8 characters)
3. [CASH]

Example change the [CHARGE] key to [CARDS]

Turn Key to PGM

1. 80 [SUBTL]
2. [C][H][A][R][G][E] [CARD]
3. [CASH]

Edit